











sparse output of the sensors enable a straightforward solution to this balancing problem, which challenges conventional imaging based systems. A solution to balancing small objects using standard image sensors requires running at greater than 1kHz frame rate. Even at the relatively low spatial resolution of  $128 \times 128 = 16$  k-pixels of the DVS sensors, image analysis requires processing pixels at a rate of  $2 \cdot 16k \cdot 1k = 32M$  pixels/second for data acquisition, which would saturate a USB2.0 hub. Log conversion for temporal contrast extraction and subtraction against stored values to obtain event-like equivalents to the DVS output would require several hundred MIPs of processing before the remaining processing described here. Quantization noise at the low end of the conversion scale would limit low light performance severely, as would the 1ms exposure times, necessitating bright and uniform lighting. The use of embedded AER sensors and event-driven methods for computation has simplified and reduced the cost of implementing this demonstration, and has shown the advantages of the event-driven style of computation used in brains.

## References

- [1] Available: <http://www.youtube.com/watch?v=lwvTyC7m4LQ>
- [2] A  $128 \times 128$  120dB 15us Latency Asynchronous Temporal Contrast Vision Sensor, (2007) Lichtsteiner, P., C. Posch and T. Delbruck. IEEE Journal of Solid State Circuits, Feb. 2008, 43(2) 566-576.
- [3] Available: <http://siliconretina.ini.uzh.ch>
- [4] J. Conradt, M. Cook, R. Berner, P. Lichtsteiner, R.J. Douglas, T. Delbruck, "A Pencil Balancing Robot using a Pair of AER Dynamic Vision Sensors" 2009 IEEE International Symposium on Circuits and Systems (ISCAS), 2009, 781-785.